

**DRIVE CIRCUIT FOR A SYNCHRONOUS RECTIFIER,
METHOD OF PROVIDING DRIVE SIGNALS THERETO AND
POWER CONVERTER INCORPORATING THE SAME**

Inventor: Thomas G. Wang
3417 Spring Mountain Drive
Plano, Texas 75025
County: Collin
Citizenship: P.R. China

Assignee: Tyco Electronics Power Systems, Inc.
3000 Skyline Drive
Mesquite, Texas 75149
A Nevada Corporation

CERTIFICATE OF EXPRESS MAIL
I hereby certify that this correspondence, including the attachments listed, is being deposited
with the United States Postal Service, Express Mail - Post Office to Addressee, Receipt No.
EV 316264545 US in an envelope addressed to
Commissioner for Patents, Alexandria, VA 22313, on the date shown below.
3/16/04 DEBBIE S2NATDER
Date of Mailing Typed or printed name of person mailing
[Signature]
Signature of person mailing

Hitt Gaines, P.C.
P.O. Box 832570
Richardson, Texas 75083-2570
(972) 480-8800

**DRIVE CIRCUIT FOR A SYNCHRONOUS RECTIFIER,
METHOD OF PROVIDING DRIVE SIGNALS THERETO AND
POWER CONVERTER INCORPORATING THE SAME**

TECHNICAL FIELD OF THE INVENTION

[0001] The present invention is directed, in general, to power converters and, more specifically, to a transition-isolating drive circuit, a method of providing drive signals to a synchronous rectifier and a power converter incorporating the same.

BACKGROUND OF THE INVENTION

[0002] In general, the demand for smaller electronic circuit modules having more features or capabilities than their predecessors has been increasing. This is especially true in the case of power converters. A power converter is a power processing circuit that converts an input voltage waveform into a specified output voltage waveform. In many applications requiring a DC output, switched-mode DC/DC power converters are frequently employed to advantage wherein both high conversion density and converter efficiency are key design requirements.

[0003] These switched-mode DC/DC power converters generally include an inverter, an isolation transformer and a rectifier on a secondary side of the isolation transformer. The inverter

typically includes a main power switch employing MOSFETs to convert a DC input voltage to an AC voltage. Then, the isolation transformer transforms this input AC voltage to an output AC voltage, and the rectifier generates the desired DC voltage at the output of the power converter. The main power switch and rectifier switches are usually operated at relatively high switching frequencies (200-300kHz). This allows the use of smaller components such as inductors and capacitors within the power converter.

[0004] Conventionally, the rectifier may include a plurality of rectifier switches (e.g., MOSFETs acting as synchronous rectifier switches) that alternately conduct the converter output load current in response to a rectifier drive signal or circuit. A problematic operating condition arises when the rectifier drive circuit does not provide a "CLOSED" or "ON" condition of the synchronous rectifier switches that allows for balanced conduction and switching losses. A particularly troubling condition exists when the rectifier drive circuit does not adequately compensate for the Miller effect or noise couplings associated with the synchronous rectifier switches, thereby assuring that they are not conducting when directed to be "OPEN" or "OFF". This could lead to a simultaneous conduction where the synchronous rectifier switches produce a momentary short circuit across the power converter. This condition reduces converter efficiency through power loss and

causes increased component stress even to the point of component failure.

[0005] Accordingly, what is needed in the art is a synchronous rectifier drive circuit that addresses these limitations.

SUMMARY OF THE INVENTION

[0006] To address the above-discussed deficiencies of the prior art, the present invention provides a transition-isolating drive circuit for a synchronous rectifier. In one embodiment, the transition-isolating drive circuit includes drive switches coupled to a transformer winding and configured to provide drive signals for the synchronous rectifier. Additionally, the transition-isolating drive circuit also includes a conduction-inhibiting circuit, coupled to the drive switches, that increases a turn-off voltage of the drive signals to a predetermined level.

[0007] In another aspect, the present invention provides a method of providing drive signals to a synchronous rectifier. The method includes employing an input voltage from a transformer winding to provide drive signals, and increasing a turn-off voltage of the drive signals to a predetermined level.

[0008] The present invention also provides, in yet another aspect, a power converter, including a main power switch coupled to a DC voltage source, a transformer coupled to the main power switch and a synchronous rectifier coupled to the transformer that provides a converter output. The power converter also includes a transition-isolating drive circuit for the synchronous rectifier, having drive switches coupled to a winding of the transformer and configured to provide drive signals for the synchronous rectifier.

The power converter also includes a conduction-inhibiting circuit, coupled to the drive switches, that increases a turn-off voltage of the drive signals to a predetermined level.

[0009] The foregoing has outlined preferred and alternative features of the present invention so that those skilled in the art may better understand the detailed description of the invention that follows. Additional features of the invention will be described hereinafter that form the subject of the claims of the invention. Those skilled in the art should appreciate that they can readily use the disclosed conception and specific embodiment as a basis for designing or modifying other structures for carrying out the same purposes of the present invention. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] For a more complete understanding of the present invention, reference is now made to the following descriptions taken in conjunction with the accompanying drawings, in which:

[0011] FIGURE 1 illustrates a circuit diagram of an embodiment of a power converter constructed in accordance with the principles of the present invention;

[0012] FIGURE 2 illustrates a circuit diagram of a secondary stage containing an embodiment of a transition-isolating drive circuit constructed in accordance with the principles of the present invention;

[0013] FIGURE 3 illustrates switching waveforms showing selected voltages associated with the transition-isolating drive circuit of FIGURE 2; and

[0014] FIGURE 4 illustrates drive waveforms showing an exemplary transition isolation zone associated with a transition-isolating drive circuit.

DETAILED DESCRIPTION

[0015] Referring initially to FIGURE 1, illustrated is a circuit diagram of an embodiment of a power converter, generally designated 100, constructed in accordance with the principles of the present invention. The power converter 100 includes a primary stage 105, a transformer TR having primary and secondary transformer windings PRI, SEC and a secondary stage 110. In the illustrated embodiment, the power converter 100 is exemplary of a bridge topology power converter. Alternative embodiments may employ other self-driven synchronous rectifying topologies such as forward or flyback.

[0016] The primary stage 105 is coupled to a DC voltage source V_{in} and includes first and second main power switches Q1, Q2 that are coupled to the primary transformer winding PRI and driven by a complementary duty cycle driver 106. The primary stage 105 also includes first and second primary capacitors C1, C2 that are coupled to the first and second main power switches Q1, Q2 and the primary transformer winding PRI. The secondary stage 110, which provides a converter output voltage V_{out} , is coupled to the secondary transformer winding SEC and includes a synchronous rectifier 115 having first and second synchronous switches Q_A , Q_B , an output inductor L_o and an output capacitor C_o . The secondary stage 110 also includes a transition-isolating drive circuit 120 coupled to the first and second synchronous switches Q_A , Q_B .

[0017] The complementary duty cycle driver 106 employs a duty cycle of about 50% to drive the first and second main power switches Q1, Q2 alternatively into conduction. This action, in conjunction with that of the first and second primary capacitors C1, C2, places a square-wave voltage across the primary transformer winding PRI, inducing a similar voltage across the secondary transformer winding SEC. The first and second synchronous switches Q_A, Q_B alternately conduct to provide a load current I_L at the converter output voltage Vout. If the first synchronous switch Q_A is conducting, the load current I_L flows from the center-tap of the secondary transformer winding SEC and returns through its top half-winding. Similarly, when the second synchronous switch Q_B is conducting, the load current I_L flows from the center-tap of the secondary transformer winding SEC and returns through its bottom half-winding.

[0018] The transition-isolating drive circuit 120 includes drive switches that are coupled to the secondary transformer winding SEC and configured to provide first and second drive signals DRIVEA, DRIVEB for the synchronous rectifier 115. The transition-isolating drive circuit 115 also includes a conduction-inhibiting circuit, coupled to the drive switches, that increases a turn-off voltage of the first and second drive signals DRIVEA, DRIVEB to a predetermined level. Proper selection of this predetermined level provides a transition isolation zone that prevents or substantially

reduces simultaneous conduction of the first and second synchronous switches Q_A , Q_B during a transition period when one is turning off and the other is turning on.

[0019] Turning now to FIGURE 2, illustrated is a circuit diagram of a secondary stage, generally designated 200, containing an embodiment of a transition-isolating drive circuit constructed in accordance with the principles of the present invention. The secondary stage 200 may be employed as the secondary stage 110, as was discussed with respect to FIGURE 1, or as a secondary stage in another embodiment of an appropriate power converter. The secondary stage 200, which provides a converter output voltage V_{out} and is coupled to a secondary transformer winding SEC, includes first and second synchronous switches Q_A , Q_B , an output inductor L_o and an output capacitor C_o , as before. The secondary stage 200 also includes a transition-isolating drive circuit 205 coupled to the first and second synchronous switches Q_A , Q_B and the secondary transformer winding SEC. General operation of the secondary stage 200 parallels that of the secondary stage 110 as was discussed with respect to FIGURE 1.

[0020] The transition-isolating drive circuit 205 includes first and second drive switches Q_{DA} , Q_{DB} , which are coupled to the secondary transformer winding SEC employing first and second isolation capacitors C_{D1} , C_{D2} and to the first and second synchronous switches Q_A , Q_B , respectively. The transition-isolating drive

circuit 205 also includes a conduction-enhancing circuit 210 having a resistor R coupled to a bias voltage V_{CC} and a conduction-enhancing zener diode Z_c , which provides a conduction-enhancing voltage V_g of the polarity shown. The transition-isolating drive circuit 205 further includes a conduction-inhibiting circuit 215 having first and second blocking diodes D_1 , D_2 series coupled to first and second conduction-inhibiting zener diodes Z_a , Z_b , which respectively provide first and second conduction-inhibiting voltages V_A , V_B of the polarities shown.

[0021] The first synchronous switch Q_A is conducting (i.e., closed) when the secondary transformer winding SEC provides a secondary voltage V_{PP} having a polarity shown. At this time, the first drive switch Q_{DA} is also conducting and provides a first drive signal DRIVEA to the gate of the first synchronous switch Q_A that is positive thereby assuring it is in a conducting state. This positive gate signal is the conduction-enhancing voltage V_g , provided by the conduction-enhancing circuit 210, that limits a turn-on voltage of the first drive signal DRIVEA to a predetermined level. Alternatively, the second synchronous switch Q_B and the second drive switch Q_{DB} are non-conducting (i.e., open) during this time. The second drive switch Q_{DB} provides a second drive signal DRIVEB to the gate of the second synchronous switch Q_B that is negative thereby assuring it is in a non-conducting state. This negative gate signal is the second conduction-inhibiting voltage

V_B , provided by the conduction-inhibiting circuit 215, that increases a turn-off voltage of the second drive signal DRIVEB to a predetermined level. The predetermined level provided by the conduction-enhancing circuit 210 may be a different level than the predetermined level provided by the conduction-inhibiting circuit 215. For example, the conduction-enhancing circuit 210 may provide a 10 volt level, and the conduction-inhibiting circuit 215 may provide a two or three volt level.

[0022] Analogously, the second synchronous switch Q_B is conducting when the secondary transformer winding SEC provides a secondary voltage V_{PP} having a polarity opposite to that shown. At this time, the second drive switch Q_{DB} is also conducting and provides a second drive signal DRIVEB to the gate of the second synchronous switch Q_B that is positive, thereby assuring it is in a conducting state. This positive gate signal is again the conduction-enhancing voltage V_G provided by the conduction-enhancing circuit 210. Alternatively, the first synchronous switch Q_A and the first drive switch Q_{DA} are non-conducting during this time. The first drive switch Q_{DA} provides a first drive signal DRIVEA to the gate of the first synchronous switch Q_A that is negative thereby assuring it is in a non-conducting state. This negative gate signal is the first conduction-inhibiting voltage V_A provided by the conduction-inhibiting circuit 215. In the illustrated embodiment, the first and second conduction-inhibiting

voltages V_A , V_B are substantially equal. Of course, they may differ if required by another embodiment.

[0023] Turning now to FIGURE 3 and with continued reference to FIGURE 2, illustrated are switching waveforms, generally designated 300, showing selected voltages associated with the transition-isolating drive circuit 205 of FIGURE 2. The switching waveforms 300 include a waveform of a transformer output voltage V_{SECA} , a waveform of a first drive switch drain voltage V_{DA} and a waveform of the first drive signal DRIVEA.

[0024] The first synchronous switch Q_A and the first drive switch Q_{DA} are conducting during a time period A when the transformer output voltage V_{SECA} is positive and equal to the secondary voltage V_{PP} . The first drive switch drain voltage V_{DA} is equal to a difference between the secondary voltage V_{PP} and the first conduction-inhibiting voltage V_A . This difference produces an offset and is due to the first isolation capacitor C_{D1} maintaining a voltage level equal to the first conduction inhibiting voltage V_A . This first conduction-inhibiting voltage V_A was provided across the first conduction-inhibiting zener diode Z_a during a previous time period B, when the first blocking diode $D1$ was conducting and not blocking as it does in the time period A. The gate of the first drive switch Q_{DA} is maintained at the conduction-enhancing voltage V_G thereby providing a first drive

signal DRIVEA substantially equal to the conduction-enhancing voltage V_G .

[0025] During the time period B, the first synchronous switch Q_A and the first drive switch Q_{DA} are turned off and the second synchronous switch Q_B and the second drive switch Q_{DB} are turned on. The first drive switch drain voltage V_{DA} is equal to a negative value of the first conduction-inhibiting voltage V_A due to the offset voltage maintained by the first isolation capacitor C_{D1} . The first drive signal DRIVEA then provides this negative value of the first conduction-inhibiting voltage V_A via conduction through a first drive switch body diode BD_{QDA} to the gate of the first synchronous switch Q_A . This allows the first drive signal DRIVEA, in conjunction with the second drive signal DRIVEB, to provide a transition isolation zone for the first and second synchronous switches Q_A , Q_B that substantially prevents them from simultaneously conducting during a synchronous switch transition.

[0026] Turning now to FIGURE 4, illustrated are drive waveforms, generally designated 400, showing an exemplary transition isolation zone associated with a transition-isolating drive circuit. The drive waveforms 400 include first and second drive signals DRIVEA, DRIVEB. Also shown are a threshold voltage V_T , first and second conduction-inhibiting voltages V_A , V_B that are substantially equal, a conduction-enhancing voltage level V_G and a transition isolation zone TIZ.

[0027] The drive waveforms 400 show the first drive signal DRIVEA turning off a first synchronous switch Q_A , and the second drive signal DRIVEB turning on a second synchronous switch Q_B . The respective drive signals turn off and turn on their respective synchronous switches at about the threshold voltage V_T . In the illustrated embodiment, the first and second drive signals DRIVEA, DRIVEB intersect at a level below the threshold voltage V_T , thereby assuring that turn-off of the first synchronous switch Q_A occurs before turn-on of the second synchronous switch Q_B . This action provides the transition isolation zone TIZ, which acts as a guard interval to prevent simultaneous conduction of the first and second synchronous switches Q_A , Q_B . The width of the transition isolation zone TIZ may be set by appropriately adjusting values of the first and second conduction-inhibiting voltages V_A , V_B and the conduction-enhancing voltage V_C with respect to the threshold voltage V_T .

[0028] In summary, embodiments of the present invention employing a transition-isolating drive circuit, a method of providing drive signals to a synchronous rectifier and a power converter employing the drive circuit and method have been presented. Advantages include providing an adjustable conduction-inhibiting drive voltage level that overcomes switch Miller effect and spurious noise coupling to assure that each synchronous switch remains turned off. Additionally, an adjustable conduction-enhancing drive voltage level is provided to ensure that the

synchronous switches are turned on in an efficient manner thereby balancing conduction loss and switching loss. Furthermore, a transition isolation zone is established that ensures that no short circuit condition associated with simultaneous conduction occurs during a transition time of switching between one synchronous switch and the other thereby preventing power loss and increased device stress.

[0029] Although the present invention has been described in detail, those skilled in the art should understand that they can make various changes, substitutions and alterations herein without departing from the spirit and scope of the invention in its broadest form.